

Updating FR125-III to firmware version 2.5.7

Date: January 2013

The firmware upgrade to version 2.5.6 can be performed using the LCD or the serial console cable. The update instructions are outlined below.

The procedure is as follows:

Step 1: Make a top level directory on a USB thumbdrive called "BATUpdates".

Step 2: Copy recorder.spd_ii and recorder.spd_iii into the BATUpdates directory on the thumbdrive.

Step 3: Insert the thumbdrive into a **USB** port on the FR125-III.

- a. For LCD controller, insert the LCD into the other USB port of the FR125-III

Step 4: Start the FR125-III by plugging in the power.

Step 5: When the FR125-III completes booting, stop the recorder

- a. For LCD controller, navigate to the Status menu and select State as Stopped
- b. For console, type:
stop

Step 6: Start the update

- a. For LCD controller, navigate to SW Update then press OK
- b. For console, type:
update

Step 7: Wait for the software update to complete. It takes less than a minute. Once the update is complete the unit will reboot automatically.

Please contact me if you need any help or have questions

Mark Jensen

Binary Acoustic Technology

mrj@binaryacoustictech.com

Happy Batting